

# Z-ERA11

This chapter covers the following topics:

- Description
  - Parameters
  - Return Codes
  - Subprograms
- 

## Description

Erase a document.

When the Deletion-flag is blank, the document is moved to the Wastebasket of the cabinet. When the Deletion-flag is marked, the document is erased from Con-nect and cannot be recovered.

## Parameters

| Parameter     | Format | In | Out | Remarks                                                                                                                                                                                                                  |
|---------------|--------|----|-----|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Return-code   | N2     | O  | X   | Input -1: no ET.                                                                                                                                                                                                         |
| Cabinet       | A8     | R  |     | The cabinet in which the document is to be erased.                                                                                                                                                                       |
| Password      | A8     | R  |     | The password of the above cabinet.                                                                                                                                                                                       |
| Document-name | A32    | R* |     | The name of the document to be erased. Either Document-name or ISN, not both. The parameter Document-name is reset after a successful deletion.                                                                          |
| ISN           | P8     | R* |     | The ISN of the document to be erased. Either ISN or Document-name, not both. The parameter ISN is reset after a successful deletion. You can invoke Z-DIS11 prior to Z-ERA11 to obtain the ISN for the desired document. |
| Deletion-flag | A1     | O  |     | If blank, the document is moved to the Wastebasket. If marked, the document is erased from Con-nect.                                                                                                                     |

## Return Codes

|    |                                      |
|----|--------------------------------------|
| 00 | Success                              |
| 02 | Invalid cabinet name                 |
| 03 | Password incorrect                   |
| 04 | ISN was not found                    |
| 08 | Supply either ISN or name, not both  |
| 09 | ISN does not point to correct object |
| 51 | Invalid name                         |
| 53 | Requested object does not exist      |

## Subprograms

Z-100  
Z-110  
Z-120  
Z-122  
Z-123  
Z-147  
Z-165  
Z-175  
Z-177  
Z-180  
Z-190  
Z-194  
Z-197  
Z-222  
Z-223  
Z-400  
Z-401  
Z-1200&0